

# ABM 733X-3 Process Signal Multi-Trip Transmitter

- Suitable for combinations of process inputs and outputs
- Supply voltage 24Vdc ± 10% (<4VA)
- Amelec standard 10 year guarantee

#### **TECHNICAL SPECIFICATION**

#### **FUNCTION**

Process V / I input signal Converter / Isolator High Trip: Relay de-energise on rising input. Low Trip: Relay de-energise on falling input.

#### **INPUT**

DC current / voltage can be specified in the range of: Current up to 100mA max (Passive) Voltage 0.4 to 100V max Typical input: 4 – 20mA (Passive)

#### **CLITPLIT**

DC current or voltage specified in the range of: Current up to 100mA max in Sink configuration (externally powered) Current up 22mA max Source configuration (Internally

powered)

Voltage any from 0.4 to 20V max @ up to 20mA. Typical output range: 4 - 20mA (Source)

Three Trip set points each give changeover contacts SPCO, rated at 250VAC, 2A, 100VA (resistive).

#### **CONTROLS**

Zero / Span: 15 turn potentiometers to calibrate Output. Trips: 15 turn potentiometers to set each Trip point in the full Input range.

#### **INDICATOR**

Amber Led: power ON indicator Red Led: Relay status indicators


## **PERFORMANCE**

Response time: Typically < 400mS Linearity :  $<\pm0.1\%$  Trip repeatability:  $<\pm0.1\%$  Trip settability:  $<\pm0.1\%$ 


### **PROTECTION**

Isolation 1000V RMS\*. Input/Contacts/Supply/Earth \*500VDC if RFI option (K) is specified. Internal Fuse.
Fail safe on loss of power Input over range typically at 300%.
Output Saturation 125%


#### **TERMINATION**



#### **FRONT VIEW**



### **FUNCTION BLOCK DIAGRAM**



# **ENVIROMENTAL CONDITION**

Storage temperature: - 40 to +70 °C Operating Ambient: -15 to +55 °C Relative Humidity: 5 to 95% RH

# **MOUNTING / DIMENSION**

Card 3U high 7HP wide Mounting 19" rack / 84E wide (See rack GA for details) Card weight < 200g

# **ADD ON / OPTIONS**

J : Input injection jack socket
P: Test point (Trip set point monitoring)
K: RFI protection to IEC801-3
Non standard Power supply ranges available