

ADP454EPK AC Voltage Transducer / Isolator with Dual Output

- Suitable for SIL 1, SIL 2 & SIL 3 rated (EN 61508-2) safety instrumented system (SIS) loop applications
- Supply voltages: 115Vac $\pm 20\%$
240Vac $\pm 20\%$
24Vdc $\pm 2.5V$
48Vdc $\pm 5V$
- RFI Protection to EN 61000-4-3:2006/A2:2010
- Non Smart / Non-uProcessor, Type A instrument
- AMELEC Standard 10 year warranty

APPLICATION

- Any application where AC Voltage signals need to be isolated/converted, split and re-transmitted.

TECHNICAL SPECIFICATION

INPUT

Any standard ac voltage range, up to 500Vac max
Typical: 0-100Vac, 0-220Vac or 0-440Vac
Intermediate ranges available at no extra cost on request

OUTPUTS

DC current or voltage specified in the range of:
Current up to 100mA max in Sink configuration (externally powered)
Current up to 22mA max Source configuration (Internally powered)
Voltage: any range up to 20Vdc max may be specified.
Typical output range: 2 x 4 - 20mA (Active, $\leq 550\Omega$ loads)

CONTROLS

15 turn potentiometers for each output channel.
Zero $\pm 25\%$
Span $\pm 50\%$

INDICATOR

Power ON: LED, Amber.

PERFORMANCE

Accuracy: $< \pm 0.2\%$
Response time: Typically $< 400\text{ms}$
Supply regulation: AC supply $\pm 20\%$, DC supply $\pm 10\%$
Supply consumption: $< 2\text{VA}$

TERMINATION

Input ~	1
Scn	2
Input ~	3
Scn	4
OUTPUT 2 +	5
OUTPUT 2 -	6
OUTPUT 1+	7
OUTPUT 1 -	8
Scn	9
Earth	10
Live / +	11
Neutral / -	12

FRONT VIEW



ENVIRONMENTAL CONDITION

Storage temperature: - 40 to +70 °C
Operating Ambient: -15 to +55 °C
Relative Humidity: 5 to 95% RH (Non-Condensing)
EMC: 2014/30/EU, EN 61326-1:2013 (Generic Industrial Levels)

MOUNTING / DIMENSION

Enclosure: 50w x 75h x 182d mm
Mounting: Din Rail (TS35) as std
(optional Seismic/Surface Keyhole plate, 50w x 130h mm)
Weight $< 500\text{g}$

RF Immunity

20MHz-3GHz/5.25GHz $\leq 10\text{V/m}$, 80MHz-1GHz/5.6GHz $\leq 30\text{V/m}$,
889MHz/1.75GHz $\leq 40\text{V/m}$.

Protection

Isolation: 500Vdc: Input/Output/Output/Supply/Earth.
Internal Fuse.
Input over range: typically up to 300%.
Input Open Circuit response: Downscale drive as std